

B|B

SENSORS

**Technische Daten**

| | | |
|------------------------|---|-------|
| Messwertaufnehmer | Pt1000 | |
| Genauigkeit | Klasse B | |
| Messstrom | max. 0,1 mA | |
| Messbereich | -50...+90°C | |
| Schaltungsart | 2-Leiteranschluss | |
| Verwendungsart | zur Wandmontage | |
| Material Gehäuse | Kunststoff, UV-beständig | |
| Elektrischer Anschluss | Kabeldurchführung für Anschlusskabel von 4,5...7 mm Ø | |
| Abmessungen | Breite | 64 mm |
| | Höhe | 34 mm |
| | Tiefe | 30 mm |
| Schutzart | IP54 | |

Weitere Informationen finden Sie unter shop.bb-sensors.com

B+B Thermo-Technik GmbH | Heinrich-Hertz-Straße 4 | D-78166 Donaueschingen
Fon +49 771 83160 | Fax +49 771 831650 | info@bb-sensors.com | bb-sensors.com

Außenfühler

Pt1000, 2-Leiteranschluss
Art.-Nr. 0627 0900-01



| Technical Data | | |
|---------------------------------|--------|---------------------------------------|
| Sensor | | Pt1000 |
| Accuracy | | Class B |
| Recommended measurement current | | max. 0,1 mA |
| Measuring range | | -50...+90°C |
| Connection type | | 2-wires connection |
| Areas of Application | | wall mounting |
| Material of the housing | | Plastic, UV-resistant |
| Electrical connection | | cable gland for cable of 4,5...7 mm Ø |
| Connection cable | Width | 64 mm |
| | Height | 34 mm |
| | Depth | 30 mm |
| Ingress protection | | IP54 |

Please find more information at shop.bb-sensors.com

B+B Thermo-Technik GmbH | Heinrich-Hertz-Straße 4 | D-78166 Donaueschingen
Fon +49 771 83160 | Fax +49 771 831650 | info@bb-sensors.com | bb-sensors.com

B+B
SENSORS

Outdoor Probe
Pt1000, 2-wires connection
Art.-No. 0627 0900-01